

Mug Press

Symptoms

Test Procedure

Probable Cause and Fix

Heat Press going over set temperature

1. Faulty Element/Probe assembly
2. Faulty Controller

Timer does not activate (start counting down)

Lever in down position

1. Faulty connection/loose on Controller or Micro Switch
2. Faulty Micro Switch

Timer does not reset (Buzzer does not stop)

Lever in up position

1. Micro Switch needs adjusting
2. Faulty Micro Switch

Heat Fault on Digital Display

1. Faulty Controller
2. Open circuit on Element

Probe fault on Digital Display

1. Loose connection on Controller Connector Block (Probe)
2. Faulty Element/Probe assembly

CAL fault on Digital Display

1. Controller needs recalibrating

Element not heating

Digital Display not illuminating

1. Check power supply and Fuse
2. Faulty Fuse Holder/Switch
3. Faulty wiring or Connector
4. Faulty Controller

Open circuit on Element

1. Faulty wiring or Connector
2. Faulty Element